# PRODUCT DATASHEET

# NiMH Battery Charger (CH2PC4)

**Download Instructions (multilingual)** 

# **Mini Charger**

## **ENHANCED** COMMUNICATION

 Multiple colored LED lights indicate charge status







CHARGING



DONE





BAD (PULSING)

**VERSATILE** 

• Charges 1 or 2 AA or AAA NiMH batteries



### **SAFETY TIMER**

· Ensures charger is not active for extended periods of time



# Energizer. NIMH BATTERY AA.AAA

### **Before Using Your Charger:**

Please read all instructions and cautionary markings on the battery charger, batteries, and device.

Best used with *Energizer*<sub>®</sub> NiMH batteries.

### **Product Detail:**

**Designation:** Mini Charger

Model: CH2PC4 Color: Black

Charge Capability: "AA" (1) or (2)

"AAA" (1) or (2)

Note: Do not charge (1) "AA" and (1) "AAA"

at the same time. Please refer to the instructions for orientation diagram.

**Charging Times:** 

(estimated)

:	Battery	Capacity	Estimated
)	(NiMH)	(mAh)	(time)
	AA	1300-2000	7-10 hrs
	AA	2000-2300	10-12 hrs
	AAA	500-800	8-10 hrs

Shutoff Mechanism: Timer: 15 hours Charging Current: "AA" 170-200mA

"AAA" 80-100mA

Trickle Charge: None

Input Rating: 100-240VAC, 50-60Hz, 3W

Typical Weight: 65 grams

**Dimensions (mm):** 115 x 45 x 70 (L x W x H) Safety Features: Reverse Polarity Protection

Safety Timer to Prevent Overcharge

**Bad Battery Detection** 

### **Important Notice**

This datasheet contains information specific to products manufactured at the time of its publication.

Contents herein do not constitute a warranty.